# Disclaimer. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



# Surface/DIN Mount 24 H Time Switch With Reserve

CCT15101

# Main

Product or component type	Mechanical time switch	
Number of channels	1	
Function available	Manual time changeover	

# Complementary

Device application	Building
Load type	LED lamp 200 VA Compact fluorescent lamp 200 VA
Cycle duration	24 h
Minimum interval duration	15 min
Type of setting	Manual time changeover
Power consumption in VA	1.5 VA
Maximum switching current	16 A - 230 V AC pf = 1 4 A - 230 V AC pf = 0.6
[Ue] rated operational voltage	230240 V AC at 50/60 Hz
Backup time	24 h
Mounting support	DIN rail Surface mount
9 mm pitches	4
Colour tint	Grey
Connections - terminals	Screw terminals: 12.5 mm²
Width	72 mm
Height	72 mm
Depth	51 mm

# **Environment**

Ambient air temperature for operation	-2045 °C
IP degree of protection	IP20

# **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.5 cm

Package 1 Width	8.05 cm
Package 1 Length	8.05 cm
Package 1 Weight	180 g
Unit Type of Package 2	S03
Number of Units in Package 2	48
Package 2 Height	30 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	9400 g
Unit Type of Package 3	P12
Number of Units in Package 3	1152
Package 3 Height	105 cm
Package 3 Width	80 cm
Package 3 Length	120 cm
Package 3 Weight	235 kg



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

### Environmental Data explained >

How we assess product sustainability >

☑ Environmental footprint		
Carbon footprint (kg.eq.CO2 per CR, Total Life cycle)	2	

### **Use Better**

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Not applicable, out of EU RoHS legal scope

### Use Again

○ Repack and remanufacture		
Take-back	No	